

Technical Newsletter nº 5/2013 2013-12-11

CENTRALSEC V2 FEATURES


- Arm the control panel in partial mode.

As from version 4.6 of Centralsec, it is possible to arm the control panel in a third mode: partial mode.

This mode is useful when the goal is protect some areas and the night mode isn't the best.
For ex: arm only the garage zone and continue to circulate inside the house.

The table below shows the relationship between the 3 operating modes and the type of zone selected.





	Interior zone	Peripheral Zone	Parcial Zone
Total Mode	Arm	Arm	Arm
Night Mode	Disarmed	Arm	Arm
Parcial Mode	Disarmed	Disarmed	Arm
Disarmed	Disarmed	Disarmed	Disarmed




To arm the CentralSec panel in this mode, enter the user code and immediately press the key  for 2 seconds.
The exit time starts to count and 2 beeps are heard per second.
At the end of the exit time, the CentralSec LED turns orange with two flashes.



- Alarm mode indication on OT-16S.

The mode which the alarm is armed is now indicated on the OT-16S keypad according to the following:

<p>Total Mode</p> 	<p>The symbol  remains illuminated</p>
<p>Night Mode</p> 	<p>The symbol  remains illuminated</p>

<p>Parcial Mode</p> 		<p>Both symbols  and  remain illuminated</p>
---	--	---

To make these new features possible, it is necessary to combine **CENTRALSEC V4.6** with a **C-4ZON V2.6** and an **OT-16S V2.0**.